

# Zener Diode Series 1N746 to 1N5369 Overview

Category: Electronic

written by [www.mbsm.pro](http://www.mbsm.pro) | 22 December 2025

| 0,5W         | 1W            | 5W           |
|--------------|---------------|--------------|
| 1N746 – 3V3  | 1N4728 – 3V3  | 1N5333 – 3V3 |
| 1N747 – 3V6  | 1N4729 – 3V6  | 1N5334 – 3V6 |
| 1N748 – 3V9  | 1N4730 – 3V9  | 1N5335 – 3V9 |
| 1N749 – 4V3  | 1N4731 – 4V3  | 1N5336 – 4V3 |
| 1N750 – 4V7  | 1N4732 – 4V7  | 1N5337 – 4V7 |
| 1N751 – 5V1  | 1N4733 – 5V1  | 1N5338 – 5V1 |
| 1N752 – 5V6  | 1N4734 – 5V6  | 1N5339 – 5V6 |
| 1N753 – 6V2  | 1N4735 – 6V2  | 1N5340 – 6V0 |
| 1N754 – 6V8  | 1N4736 – 6V8  | 1N5341 – 6V2 |
| 1N755 – 7V5  | 1N4737 – 7V5  | 1N5342 – 6V8 |
| 1N756 – 8V2  | 1N4738 – 8V2  | 1N5343 – 7V5 |
| 1N757 – 9V1  | 1N4739 – 9V1  | 1N5344 – 8V2 |
| 1N758 – 10V  | 1N4740 – 10V  | 1N5345 – 8V7 |
| 1N962 – 11V  | 1N4741 – 11V  | 1N5346 – 9V1 |
| 1N759 – 12V  | 1N4742 – 12V  | 1N5347 – 10V |
| 1N964 – 13V  | 1N4743 – 13V  | 1N5348 – 11v |
| 1N965 – 15V  | 1N4744 – 15V  | 1N5349 – 12v |
| 1N966 – 16V  | 1N4745 – 16V  | 1N5350 – 13v |
| 1N967 – 18V  | 1N4746 – 18V  | 1N5351 – 14V |
| 1N968 – 20V  | 1N4747 – 20V  | 1N5352 – 15V |
| 1N969 – 22V  | 1N4748 – 22V  | 1N5353 – 16V |
| 1N970 – 24V  | 1N4749 – 24V  | 1N5354 – 17V |
| 1N971 – 27V  | 1N4750 – 27V  | 1N5355 – 18V |
| 1N972 – 30V  | 1N4751 – 30V  | 1N5356 – 19V |
| 1N973 – 33V  | 1N4752 – 33V  | 1N5357 – 20V |
| 1N974 – 36V  | 1N4753 – 36V  | 1N5358 – 22V |
| 1N975 – 39V  | 1N4754 – 39V  | 1N5359 – 24V |
| 1N976 – 43V  | 1N4755 – 43V  | 1N5360 – 25V |
| 1N977 – 47V  | 1N4756 – 47V  | 1N5361 – 27V |
| 1N978 – 51V  | 1N4757 – 51V  | 1N5362 – 28V |
| 1N979 – 56V  | 1N4758 – 56V  | 1N5363 – 30V |
| 1N980 – 62V  | 1N4759 – 62V  | 1N5364 – 33V |
| 1N981 – 68V  | 1N4760 – 68V  | 1N5365 – 36V |
| 1N982 – 75V  | 1N4761 – 75V  | 1N5366 – 39V |
| 1N983 – 82V  | 1N4762 – 82V  | 1N5367 – 43V |
| 1N984 – 91V  | 1N4763 – 91V  | 1N5368 – 47V |
| 1N985 – 100V | 1N4764 – 100V | 1N5369 – 51V |

Zener diodes are essential components in voltage regulation and protection circuits. This guide provides a detailed overview of three popular power ratings: 0.5W, 1W, and 5W Zener diode series, covering part numbers from 1N746 to 1N5369 and voltage ranges from 3.3V to 100V. Whether you're designing a power supply, voltage reference, or surge protection circuit, having a complete voltage chart at your fingertips is invaluable for selecting the right component.