

# Hitachi Compressor, LBP, R134a, FL1152-RG, 1/6 Hp, 155W, série R012

Category: compressor

written by [www.mbsm.pro](http://www.mbsm.pro) | 16 January 2021

Code No.	Model	HP	Capacity (W)	Current (A)	Efficiency COP (w/w)	Voltage / Frequency
<b>R134a Models</b>						
R012001	FL 06S34-TAB	1/12	85	0.70	0.93	220V – 240V / 50Hz
R012002	FL 0739-SQ	1/10	114	0.72	1.20	
R012003	FL 0847-SD	1/8	130	0.83	1.19	
R012005	FL 1152-SB	1/6	143	0.82	1.27	
R012006	FL 1257-SR	1/5	160	0.90	1.25	
R012007	FL 14S62-TAD	1/5	175	0.95	1.30	
R012008	FL 1568-SQ	1/4	200	1.11	1.30	
R012009	FL 20S88-TAC	1/3	255	1.50	1.25	
R012010	FL1888-SE	1/3	245	1.51	1.25	
<b>R600a Models</b>						
	CL 0545-SZ	1/12	62	0.70	1.12	220V – 240V / 50Hz
	CL 1297-SA	1/5	156	0.90	1.46	
	CL 1310-SA	1/5+	163	0.95	1.48	
<b>R600a Models (Inverter)</b>						
	CL 1588-DZ	1/6	134	0.83	1.62	220V – 240V / 50Hz
	CL 1610-DL	1/5	160	0.90	1.65	

Private Picture Copyright: [WWW.MBSM.PRO](http://WWW.MBSM.PRO)

Code No.	Model	HP	Capacity (W)	Current (A)	Efficiency COP (w/w)	Voltage / Frequency
<b>R134a Models</b>						
R012001	FL 06S34-TAB	1/12	85	0.70	0.93	220V – 240V / 50Hz
R012002	FL 0739-SQ	1/10	114	0.72	1.20	
R012003	FL 0847-SD	1/8	130	0.83	1.19	
R012005	FL 1152-SB	1/6	143	0.82	1.27	
R012006	FL 1257-SR	1/5	160	0.90	1.25	
R012007	FL 14S62-TAD	1/5	175	0.95	1.30	
R012008	FL 1568-SQ	1/4	200	1.11	1.30	
R012009	FL 20S88-TAC	1/3	255	1.50	1.25	
R012010	FL1888-SE	1/3	245	1.51	1.25	
<b>R600a Models</b>						
	CL 0545-SZ	1/12	62	0.70	1.12	220V – 240V / 50Hz
	CL 1297-SA	1/5	156	0.90	1.46	
	CL 1310-SA	1/5+	163	0.95	1.48	
<b>R600a Models (Inverter)</b>						
	CL 1588-DZ	1/6	134	0.83	1.62	220V – 240V / 50Hz
	CL 1610-DL	1/5	160	0.90	1.65	

Private Picture Copyright: [WWW.MBSM.PRO](http://WWW.MBSM.PRO)

HITACHI FL1152-RG

220V 50/60Hz OIL 2010.04.27



SERIAL NO. 00542 HFC-134a

⚠ WARNING | HIGH TEMPERATURE  
ELECTRIC SHOCK  
DO NOT TOUCH H24

60Hz	FL1462-P*	6.2		180	154	615	350	St		RSR	10.5	200
	FL1462-P*	6.2		210	180	717	310	St		RSCR	11.8	216
	FL1568-P*	6.8		210	180	717	310	St		RSCR	11.5	217
	FL1675-P*	7.5		233	200	795	300		OC	RSR	10.8	216
	FL1875-P*	7.5		225	193	768	300		OC	RSR	11.9	211
	FL1875-P*	7.5		255	219	871	300		OC	RSCR	11.9	216
	FL0634-U*	3.4		98	84	335	270	St		RSR	8.3	179
	FL0739-U*	3.9		114	98	389	270	St		RSR	8.3	179
	FL1052-U*	5.2		147	126	502	270	St		RSR	8.1	179
127V	FL1152-U*	5.2		155	133	529	240	St		RSR	9.0	180
60Hz	FL1262-U*	6.2		173	148	591	320	St		RSR	9.8	195
	FL1462-U*	6.2		180	154	615	350	St		RSR	10.5	200
	FL1568-U*	6.8		208	178	710	310	St		RSCR	11.5	216
	FL1568-U*	6.8		228	196	778	310	St		RSR	10.5	200
	FL1875-U*	7.5		225	193	768	300		OC	RSR	11.1	216
200V	FL1875-T*	7.5	200	232	172	683	300		OC	IR	11.1	211
50/60Hz	FL2088-T*	8.8	263	290	226	898	300		OC	IR	11.1	211
	FL0634-R*	3.4		98	84	335	270	St		RSR	8.0	179
	FL0739-R*	3.9		115	99	393	270	St		RSR	8.0	179
	FL0845-R*	4.5		122	105	417	240	St		RSR	8.7	180
220V	FL1052-R*	5.2		150	129	512	240	St		RSR	8.9	180
60Hz	FL1152-R*	5.2		155	133	529	270	St		RSR	8.1	179
	FL1262-R*	6.2		162	139	553	320	St		RSR	9.8	195
	FL1462-R*	6.2		207	178	707	300	St		RSR	10.6	196
	FL1568-R*	6.8		228	196	778	310	St		RSR	10.5	200
	FL1568-R*	6.8	181		155	618	300	St		RSCR	11.5	216
	FL1875-R*	7.5		238	204	813	300		OC	RSR	11.1	216
	FL0634-S*	3.4	95		82	324	240	St		RSCR	9.0	180
	FL0634-S*	3.4	82		70	280	270	St		RSR	7.8	179
	FL0734-S*	3.4	95		82	326	240	St		RSCR	9.0	180



Private Picture Copyright: WWW.MBSM.PRO

Mbsm\_dot\_pro\_private\_PDF\_FL1152-RGTélécharger