

S/M No:

Service Manual

Refrigerator



✓ Caution

In this manual, some parts can be changed for improving their performance without notice. So, If you need the latest parts information, please visit and refer to PPL (Parts Price List)] in Service Infromation Center. (http://svc.dwe.co.kr)

Please observe the following safety precautions in order to use safely and correctly the refrigerator and to prevent accident and danger during repair.

- Be care of an electric shock. Disconnect power cord from wall outlet and wait for more than three minutes before replacing PCB parts.
 Shut off the power whenever replacing and repairing electric components.
- 2. When connecting power cord, please wait for more than five minutes after power cord was disconnected from the wall outlet.
- 3. Please check if the power plug is pressed down by the refrigerator against the wall. If the power plug was damaged, it may cause fire or electric shock.
- 4. If the wall outlet is over loaded, it may cause fire.

 Please use its own individual electrical outlet for the refrigerator.
- 5. Please make sure the outlet is properly earthed, particularly in wet or damp area.
- 6. Use standard electrical components when replacing them.
- 7. Make sure the hook is correctly engaged.


 Remove dust and foreign materials from the housing and connecting parts.
- 8. Do not fray, damage, machine, heavily bend, pull out or twist the power cord.
- Please check the evidence of moisture intrusion in the electrical components.Replace the parts or mask it with insulation tapes if moisture intrusion was confirmed.
- 10. Do not touch the icemaker with hands or tools to confirm the operation of geared motor.
- 11. Do not let the customers repair, disassemble and reconstruct the refrigerator for themselves. It may cause accident, electric shock, or fire.
- 12. Do not store flammable materials such as ether, benzene, alcohol, chemicals, gas, or medicine in the refrigerator.
- 13. Do not put flower vase, cup, cosmetics, chemicals, etc., or container with full of water on the top of the refrigerator.
- 14. Do not put glass bottles with full of water into the freezer. The contents shall freeze and break the glass bottles.
- 15. When you scrap the refrigerator, please disconnect the door gasket first and scrap it where children are not accessible.

1. Specification

Factory No.		FRP-37	FRP-37	
Buye	er No.	FR-450	FN-450	
	Total	408L	408L	
Gross Vol. (ISO15502)	Freezer	126L	126L	
(.00.0002)	Refrigerator	282L	282L	
	Total	361L	361L	
Storage Vol. (IS015502)	Freezer	99L	99L	
(.55.5552)	Refrigerator	262L	262L	
	Width	742mm	742mm	
Net Diemension	Depth (w/o handle)	697mm	697mm	
	Height	1801mm	1801mm	
	Refrigerant type	R-134a	R-600a	
Cooling Cycle	Refrigerant charge	90g	40g	
Cooling Cycle	Evaporator type	Fin Type	Fin Type	
	Colling system	Fan cooling system	Fan cooling system	
Heater	Defrost heater	148W	180W	
пеацег	Defrost control	Automatic start & stop	Automatic start & stop	
Sensor	Defrost sensor	PBN-43	PBN-43	
Sensor	Refrigerator sensor	PBN-43	PBN-43	
	Fuse temp.	77 ℃	77 ℃	
Electronic Part	Refrigerator lamp	15w x 1ea	15w x 1ea	
	Fan motor	AC or DC (mod	del dependent)	
Net \	Weight	69kg	69kg	

1

2. Internal View



Freezer Compartment

a. Freezer shelf

b. Twist ice maker

c. Freezer temperature control knob

d. Lamp window (15W x 1ea)

e. Shelf chilled case (*option)

f. Chilled Case (*option)

Refrigerator Compartment

g. Refrigerator Shelf

h. Vegetable case*


i. Freezer pocket

j. Utility pocket

k. Jumbo pocket

l. Bottle Pocket

1. Temperature control



- 1) Freezer temperature control
- Temperature controlled by moving the lever horizontally.
- No relation with M-PCB. It just controls the cold air hole. (Low is fully open, Winter is almost close the hole.)
- 2) Refrigerator temperature control
- The dial will be changed by the TEMP button.
- Initial mode is Mid and whenever pressing TEMP button, the dial will change as follows.


Low - Mide - High - Quick - Low

- Inner real temperature controlled by sensor on/off point.
- Each sensor on/off point controls Compressor & Fan motor operation.
- Fan motor is on/off after 1minute from compressor is on/off. (Fan motor delay time is 1 minute.)

Control	Low	Mid	High	Quick
On (℃)	5.0	2.5	0.0	-
Off (°C)	3.0	0.5	-2.0	-3.0 (for 40 minute)


- 3) Quick Mode (max. time limit is 40 min.)
- When Quick mode selected, led is on.

4) Control point in each mode




2. Defrosting Mode

- 1) Determination of defrosting mode.
- Basic condition is compressor running time is 6, 8, 10 \sim 24 hours.
- Compressor runing-ratio (at every 2 hours) is 85% in the room temperature is over 35 °C.
- (The room temperature affects the compressor runing-ratio. The degree is propotional to runing-ratio.)
- Door opening time is over 2 minutes.
- Total time (Compressor is on time + off time) is 60 hours.
- Any error happens.



3. Defrosting Process

- 1) Defrost mode is active according to the condition. (operation time, any error, door openning time & etc.)
- 2) Precess




[Pre-cool]

- Control: Compressor on, Fan on, Heater off.
- Exit : When refrigerator sensor is below -4 $^{\circ}$ C. (about 20 ~ 30 minutes)

[Heater defrosting]

- Control : Compressor off, Fan off, Heater on.
- 30 seconds : Heater is on unconditionally.
- 30 minutes : When D1 errror happens. (D1 : defrost sensor is abnormal)
- 80 minutes : Maximum time limit.
- Exit : Defrost sensor is more than 10℃.



[Pause]

- Control: Compressor off, Fan off, Heater off.
- Exit : After 4 minutes.

[Fan delay]

- Control : Compressor on, Fan off, Heater off.
- Exit : After 4 minutes.

4. Prevention of compressor restart


; Compressor doesn't restart for about 6 minutes to protect compressor regardless of refrigerator sensor.

5. Initial Defrosting

; If defrosting sensor temperauture is below 3.5 °C in initial power input, normal defrosting mode starts.


6. Weak Cooling) easy action

; Adjustment of refrigerator sensor resistance value \rightarrow Change on/off temperature.



- When weak cooling in refrigerator compartment sw1 is useful.
- 3) Weak Ref. : SW1 is off. The sensor off point is -1.0 $^{\circ}$ C. (When the dial is MID step.)

Dial	SW1	Resistance value	Sensor Off point
Low	Normal (on)	R31 (31.4K)	3.0℃
LOW	Weak Ref. (off)	R31 + R32 (31.4K + 2.15K)	1.5℃
Mid	Normal (on)	R31 (31.4K)	0.5℃
IVIIC	Weak Ref. (off)	R31 + R32 (31.4K + 2.15K)	-1.0℃
High	Normal (on)	R31 (31.4K)	-2.0℃
High	Weak Ref. (off)	R31 + R32 (31.4K + 2.15K)	-3.5℃
Quick	Normal (on)	R31 (31.4K)	-3.0℃
(active for 40min.)	Weak Ref. (off)	R31 + R32 (31.4K + 2.15K)	-4.5℃



6. Error Display

- 1) How to start: Push the TEMP button 30 times. And then keep pressing the button for 5 seconds.
- 2) How to exit: Returns to normal mode after 20 seconds automatically.
- 3) Error display in detail

Error display		Explanation			Remark
Low LED is flicker	- Cause : Defrost sensor is d - Control : Defrosting is active (Heater is on for 3				
Mid LED is flicker	- Cause : Refrigerator sensor is disconnected or short. - Control : Compressor is on/off according to room temperature. R.T. ~ 10°C 11 ~ 15°C 16 ~ 29°C 35°C ~ Comp. on/off 6 / 34 (min.) 10 / 30 (min.) 16 / 24 (min.) 20 / 20 (min.)				
High LED is flicker	- Cause : Defrost mode ends (When evaporator fuse is abnormal of - Action : Need to check all d				
Quick LED is flicker	- Cause: After 2 hours' compressor runing time, defrost sensor is over -5°C (Cycle is abnormal: refrigerant leakage or block) - Action: Need to check all cycle parts.				

⁴⁾ If there is no error, all LED is off when error display.

7. Time delay of electric parts.

- 1) Normal control state: Fan motor is on/off after 1 minute from compressor on/off.
- 2) Initial plug-in : Fan motor is on after 4 minutes from compressor on.
- 3) Door opening \rightarrow closing : Fan motor is on after 20 seconds.

8. Pull Down (it is a kind of test mode)


- 1) How to start: Push the TEMP button 30 times.
- 2) How to exit
- Push the TEMP button 30 times again. or
- After 21 hours automatically ends.
- 3) Display: All LED is on.
- 4) Compressor / freezer fan & compressor cooling fan are on for 21 hours.

9. A/s Defrosting (forced defrosting)


- 1) How to start: Push TEMP button 5 times while door is open.
- 2) How to exit
- Push TEMP button 5 times while door is open again.
- 3) Display: No display.
- 4) The process is the same with the defrosting mode without pre-cool.

1. Wiring Diagram


[RSCR]




[RSIR]




2. Air Flow Diagram





3. Refrigerant Cycle Diagram



1. Freezer Louver



1) Remove screw cap on the Freezer Louver.





2) Remove 2 screws.





3) Take off the louver with driver as left figure shown.

2. Refrigerator) Control Box As.



1) Take off lamp window as left figure shown.





Disassemble refrigerator lamp.
 (15Wx1ea)





3) Unscrew which fixing the control box.






4) Unscrew which fixing the control box.






5) Take off the control box as.



No	Part Code	Part Name	Spec.	Q'ty	Remark
Α	3010519210	BOX M/PCB	PP	1	
В	Last page	PCB MAIN AS		1	1
С	Last page	CAPACITOR RUN		1	1
D	3011444901	COVER M/PCB BOX	PP	1	1
1	3017046401	EVA FIN SAS	FR-B372ET (R-134a)	1	1
_ ′	3017046440	LVATIN SAS	FRP-37(R-600a)	,	
2	3017200410	FUSE TEMP AS	FRB-4870KT	1	
3	Last page	HEATER D AS		1	
4	3012911500	HINGE *T	SCP-1 T2.3	1	
5	3011449800	COVER *T HI	PP	1	1
6	3012911420	HINGE *M AS	PO/T3.2	1	
7	3012101300	FOOT ADJ AS	PP	2	
8	3012911301	HINGE *U AS	PO/T4.0	1	
10	3011450200	COVER CAB BRKT	PP	1	
13	-	CORD POWER AS	COUNTRY DEPENDENT	1	
16	3013201700	HOSE DRN B	PE FRB-5350NT	1	
17	3012405820	GRILLE	PCM B GRADE T0.4	1	
19	3016805500	DRYER AS	FRM(P)-371	1	
20	3014434021	PIPE WICON AS	FRM-37	1	
22	3011801310	FAN C AS	110(FAN), 3.17(SHAFT)	1	
23	Last page	MOTOR C		1	
24	3012004400	FIXTURE C MOTR	SUS	1	
26	3011117511	CASE VAPORI	PP	1	
27	Last page	COMPRESSOR		1	
28	Last page	SWITCH P RELAY AS		1	
29	-	COVER RELAY	-	1	


⁻ Some parts can be chaged for improving their perfomance without notice.



No	Part Code	Part Name	Spec.	Q'ty	Remark
37	Last page	MOTOR F AS		1	
37-1	3012007901	FIXTURE MOTR B	PP	1	1
37-2	Last page	MOTOR F		1	1
37-3	3011802200	FAN	ABS OD3.17XD110	1	
39	3018911500	LOUVER F AS	FRM(P)-371	1	
44	3017822500	SHELF F	WIRE+DECO	1	Option
44	3017821600	STILLI T	HIPS	7	Option
45	3011163910	CASE TWIST ICE AS	FRM(P)-371G/H	1	
50	3018100010	SWITCH DR	2 BUTTON/4P,DSD-5	1	
53	3011452801	COVER R LAMP AS	FRP-371	1	
53-1	3011450100	COVER R LAMP	HIPS	1	
53-2	3017900842	SOCKET F/R LAMP AS	-	1	
53-3	3013600050	LAMP AS	110-127V/15W	1	
55-5	3013600020	LAIVIF AS	220-240V/15W	7	
53-4	3014800411	SENSOR R1 AS	ABS	1	
59	3015505200	WINDOW F LAMP	PP	1	
60	3011439500	COVER CUBIC DUCT	HIPS	2	
62	3018911600	LOUVER R *S *L AS	FRM(P)-371	1	
64	3018911700	LOUVER R *S *R AS	FRM(P)-371	1	
65	3017821800	SHELF CHILD (AS)	GPPS(MOLD)	1	Option
05	3017823110	STILLE OFFILE (AS)	GLASS(NO PRINT)	1	Орион
66	3011162300	CASE CHILD	GPPS(MOLD)	1	
	3017822400		WIRE+DECO		
67	3017822000	SHELF R (AS)	GPPS(MOLD)	1	Option
	3017823010		GLASS(NO PRINT)		
68	3011451400	COVER V/CASE	GPPS(MOLD)	1	
	3011162400		CRYSTAL, 4501Series	1	Option
69	3011162420	CASE VEGETB	BLUE, 4501Series	,	Οριιστί
	3011162500	JOHOL VEGETO	CRYSTAL, HALF-WIDE	2	Option
	3011162520		BLUE, HALF-WIDE		Орион

⁻ Some parts can be chaged for improving their perfomance without notice.

4 /



4501.. series (Hidden Handle)

No	Part Code	Part Name	Spec.	Q'ty	Remark
80	30100894L0	ASSY F DR TOTAL	-	1	
80-1	3012301420	GASKET F DR AS	PVC	1	
81	3019013500	POCKET F	HIPS	2	
90	30100334J0	ASSY R DR TOTAL	-	1	
90-1	3012301720	GASKET R DR AS	PVC	1	
93	3011162100	CASE EGG	GPPS FRM(P)-371	1	
94	3019013100 POCKET SM		HIPS(FRP-371H)	(H) 4	
95	3012509600	GUIDE POKT	ABS 1		
96	3019013300	POCKET JUMBO	HIPS (SILK)	1	
97	3019013400	POCKET BOTL	HIPS	1	
98	3014229020	PANEL F CONTL AS	FRP-371	1	
98-1	3015505300	WINDOW FCP	GPPS	1	
98-2	3014228600	PANEL CONTL F	ABS	1	
98-3	3014301170	PCB *F AS	FRP-371	1	


⁻ Some parts can be chaged for improving their perfomance without notice.

(80-1) (90-1) 90

4502.. series (Handle Packing)

				Jz Series (Tiari	uio i doitiiig /
No	Part Code	Part Name	Spec.	Q'ty	Remark
80	3010089460	ASSY F DR TOTAL	-	1	
80-1	3012301420	GASKET F DR AS	PVC	1	
81	3019013500	POCKET F	HIPS	2	
90	3010033440	ASSY R DR TOTAL	-	1	
90-1	3012301720	GASKET R DR AS	PVC	1	
93	3011162100	CASE EGG	GPPS FRM(P)-371	1	
94	3019013100	POCKET SM	HIPS(FRP-371H)	4	
95	3012509600	GUIDE POKT	ABS 1		
96	3019013300	POCKET JUMBO	HIPS (SILK)	1	
97	3019013400	POCKET BOTL	HIPS	1	
98	3014229020	PANEL F CONTL AS	FRP-371	1	
98-1	3015505300	WINDOW FCP	GPPS	1	
98-2	3014228600	PANEL CONTL F	ABS	1	
98-3	3014301170	PCB *F AS	FRP-371	1	
99	3014001801	PACKING HNDL AS	FRP-372/3	1	

⁻ Some parts can be chaged for improving their perforance without notice.



4506.. series (Grip Handle)

4506 series (Grip i				
Part Code	Part Name	Spec.	Q'ty	Remark
3010084700	ASSY F DR	-	1	
3012301420	GASKET F DR AS	PVC	1	
3019013500	POCKET F	HIPS	2	
3012624300	HANDLE F	ABS	1	
3011611300	DECO F HNDL A	ABS	1	
3011611410	DECO F HNDL B	ABS+SPRAY	1	
3010084800	ASSY R DR	-	1	
3012301720	GASKET R DR AS	PVC	1	
3012624400	HANDLE R	ABS	1	
3011611500	DECO R HNDL	ABS	1	
3011162100	CASE EGG	GPPS FRM(P)-371	1	
3019013100	POCKET SM	HIPS(FRP-371H)	4	
3012509600	GUIDE POKT	ABS	1	
3019013300	POCKET JUMBO	HIPS (SILK)	1	
3019013400	POCKET BOTL	HIPS	1	
3014229020	PANEL F CONTL AS	FRP-371	1	
3015505300	WINDOW FCP	GPPS	1	
3014228600	PANEL CONTL F	ABS	1	
3014301170	PCB *F AS	FRP-371	1	
	3010084700 3012301420 3019013500 3012624300 3011611300 3011611410 3010084800 3012301720 3012624400 3011611500 3011162100 3019013100 3019013300 3019013400 3014229020 3015505300 3014228600	3010084700 ASSY F DR 3012301420 GASKET F DR AS 3019013500 POCKET F 3012624300 HANDLE F 3011611300 DECO F HNDL A 3011611410 DECO F HNDL B 3010084800 ASSY R DR 3012301720 GASKET R DR AS 3012624400 HANDLE R 3011611500 DECO R HNDL 3011162100 CASE EGG 3019013100 POCKET SM 3012509600 GUIDE POKT 3019013300 POCKET JUMBO 3019013400 POCKET BOTL 3014229020 PANEL F CONTL AS 3015505300 WINDOW FCP 3014228600 PANEL CONTL F	3010084700 ASSY F DR - 3012301420 GASKET F DR AS PVC 3019013500 POCKET F HIPS 3012624300 HANDLE F ABS 3011611300 DECO F HNDL A ABS 3011611410 DECO F HNDL B ABS+SPRAY 3010084800 ASSY R DR - 3012301720 GASKET R DR AS PVC 3012624400 HANDLE R ABS 3011611500 DECO R HNDL ABS 3011162100 CASE EGG GPPS FRM(P)-371 3019013100 POCKET SM HIPS(FRP-371H) 3019013300 POCKET JUMBO HIPS (SILK) 3019013400 POCKET BOTL HIPS 3014229020 PANEL F CONTL AS FRP-371 3015505300 WINDOW FCP GPPS 3014228600 PANEL CONTL F ABS	3010084700 ASSY F DR - 1 3012301420 GASKET F DR AS PVC 1 3019013500 POCKET F HIPS 2 3012624300 HANDLE F ABS 1 3011611300 DECO F HNDL A ABS 1 3011611410 DECO F HNDL B ABS+SPRAY 1 3010084800 ASSY R DR - 1 3012301720 GASKET R DR AS PVC 1 3012624400 HANDLE R ABS 1 3011611500 DECO R HNDL ABS 1 301162100 CASE EGG GPPS FRM(P)-371 1 3019013100 POCKET SM HIPS(FRP-371H) 4 3019013300 POCKET JUMBO HIPS (SILK) 1 3019013400 POCKET BOTL HIPS 1 3014229020 PANEL F CONTL AS FRP-371 1 3014228600 PANEL CONTL F ABS 1

⁻ Some parts can be chaged for improving their perfomance without notice.

No	Part Name	Part Code	Spec.	Q'ty	Remark
В	PCB MAIN AS	3014301070	AC 220-240V, BASIC	1	
		3014301080	AC 220-240V, WIRE SHELF		*Refrigerator compartment shlelf is wire.
		3014302070	AC 110V, BASIC		
		30143H9060	EUROPE, TAIWAN, CUBA		Europe, Taiwan, Cuba (R600a or unique country)
С	CAPACITOR RUN	3016406300	230VAC/10	1	HEL23YG-9
		3016405900	350VAC/5 ¼F (WIRE, P2)		HPL23YH-5
		3016406100	400VAC/5 یراF (WIRE, P2)		HPL25YH-5-K
		3016405020	250VAC/12 µF (WIRE,P2)		JX58LHE3, MSA151-L1B
		3016405800	350VAC/4 ¼F (WIRE, P2)		JX58LHP4
		3016406000	400VAC/4 یدا (WIRE, P2)		MQ98NAEM
3	HEATER D AS	3012807802	FRM(P)-372,110V/148W	1	110-127V
		3012807702	FRM(P)-372,220-240V/148W		220-240V
	HEATER SHEATH AS	3012823110	FRM(P)-372,220-240V/180W		R600a, 220-240V
23	MOTOR C	3015909900	AC 110V	1	
		3015910000	AC 220V/60Hz		
		3015909800	AC 220-240V		
		3015906850	DC 10V		Europe, Taiwan, Cuba (R600a or unique country)
27	COMPRESSOR	3953123R90	HEL23YG-9	1	110V/50Hz, Jamaica
		<i>3956123S50</i>	HPL23YH-5		
		<i>3956125S51</i>	HPL25YH-5-K		Country dependent
		3954125G50	HSL25YE-5		
		<i>3953158J30</i>	JX58LHE3		110V/60Hz
		<i>3956158J40</i>	JX58LHP4		220V/60Hz
		3956198M50	MQ98NAEM		Europe (R600a, 220-240V/50Hz)
		3956151D20	MSA151-L1B		Taiwan
28	SWITCH P RELAY AS	3018118150	783NHB, S068	1	HEL23YG-9
		3018116610	181SHB, S330		HPL23YH-5
		3018118250	265NHB, S220		HPL25YH-5-K
		3018119940	276THB, S220		HSL25YE-5
		3018118220	317NHB, S068		JX58LHE3
		3018118230	213THB, S220		JX58LHP4
		3018133710	4TM174TFB, P330MD2		MQ98NAEM
		3018118270	4TM308RHB,100MD2		MSA151-L1B
37	MOTOR F AS	3015900931	110V/50, 60HZ	1	
		3015900951	220V/60HZ		
		3015900941	220-240V/50HZ		
		3015900952	DC 12V		Europe, Taiwan, Cuba (Unique country)
37-2	MOTOR F	3015900741	110V/50, 60HZ	1	
		3015900701	220V/60HZ		
		3015900731	220-240V/50HZ		
		3015905330	DC 12V		Europe, Taiwan, Cuba (Unique country)