

Mbsm.pro, Compressor , Tecumseh

 mbsm.pro/62806.html

March 5, 2025



<https://www.tecumseh.com/ProductFamily/AE/Catalog/product-type/compressors>

AZ Fridge Freezer Compressor Model AE R134



MODEL	HP	BTU/h	APPL.	ENGINE	LRA	FLORIDA	PRICE
AZ1327Y	1/15	229	PSL	RSIR	6,70	0,50	N / A
AZ1320Y	1/20	194	PSL	RSIR	5:30 p.m.	0,48	N / A
AZ1330Y	1/8	270	PSL	RSIR	6.46	0,55	N / A
AZ1335Y	1/8	317	PSL	RSIR	8:30 am	0,73	N / A
AZ1340Y	1/5	358	PSL	RSIR	6,90	0,75	N / A
AZ1350Y	1/5	409	PSL	RSIR	8.70	0,77	N / A
AE1320Y	1/20	194	PSL	RSIR	5.40	0,54	N / A
AE1330Y	1/8	270	PSL	RSIR	5.44	0,55	N / A
AE1340Y	1/6	375	PSL	RSIR	7.00	0,77	N / A
AE1350Y	1/6	461	PSL	RSIR	12h00	0,90	N / A
AE1360Y	1/5	539	PSL	RSIR	10.00	1,00	N / A
AE1370Y	1/5	635	PSL	RSIR	12h60	1.17	N / A
AE1390Y	1/4	860	PSL	RSIR	14.10	1.28	N / A
AE2370Y	1/5	631	PSL	CSIR	6,50	1.18	N / A
AE2390Y	1/4	809	PSL	CSIR	9h20	1.40	N / A
AE2410Y	1/3	921	PSL	CSIR	12.75	2,00	N / A

AE2413Y	3/8	1 126	PSL	RSE	12,90	1.40	N / A
AEA2415Y	1/2	1 262	PSL	RSE	11h60	1.34	N / A
AE2417Y	1/6	1 706	RAP	RSIR	11:50 a.m.	1,60	N / A
AE2425Y	1/5	2 491	RAP	RSIR	13h60	2.20	N / A
AE3440Y	3/8	3 634	RAP	RSIR	11:30 a.m.	3,00	N / A
AE4425Y	1/5	2 388	RAP	CSIR	10h70	2.15	N / A
AE4430Y	1/3	2 798	RAP	CSIR	12h00	2,50	N / A
AE4435Y	3/8	3 078	RAP	CSIR	14.10	2,70	N / A
AE4440Y	1/2	3 668	RAP	CSIR	14h70	3.10	N / A
AE4448Y	1/2	4 060	RAP	CSIR	23,90	3.45	N / A
AE4459Y- SR	1/2	4 947	RAP	RSE	15h70	3,00	N / A
AE7415Y	1/4	1 259	MBP	CSIR	11:50 a.m.	1,82	N / A
AE7423Y	1/3	1 958	MBP	CSIR	18h50	2.28	N / A
AE7430Y	1/2	2 542	MBP	RSE	12.75	2.18	N / A
AE9437Y- SR	5/8	3 139/5 732	MBP/RAP	RSE	16h30	2,64/3,50	N / A

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE1345A- FZ1A</u>	LBP	220-240V 1PH 50Hz	1/6 HP	R-401A	4.24
<u>AE1360A- FZ1A</u>	LBP	220-240V 1PH 50Hz	1/5 HP	R-401A	6.12
<u>AE1370A- FZ1A</u>	LBP	220-240V 1PH 50Hz	1/4 HP	R-401A	6.69
<u>AE1380A- GS1B</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/4 HP	R-401A	7.56
<u>AE1390A- FZ1B</u>	LBP	220-240V 1PH 50Hz	1/4 HP	R-401A	8.02

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE1390Y-AA1A</u>	LBP	115V 1PH 60Hz	1/5 HP	R-134a, R-513A	8.02
<u>AE1390Y-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/5 HP	R-134a	8.02
<u>AE1410A-FZ1B</u>	LBP	220-240V 1PH 50Hz	1/3 HP	R-401A	8.85
<u>AE1420Z-FZ1B</u>	LBP	220-240V 1PH 50Hz	1/2 HP	R-404A	9.35
<u>AE2390Y-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/5 HP	R-134a	8.02
<u>AE2410A-AA1A</u>	LBP	115V 1PH 60Hz	1/4 HP	R-12	9.39
<u>AE2410P-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/4 HP	R-454C, R-455A	5.02
<u>AE2410U-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/4 HP	R-290	6.12
<u>AE2410Y-AA1A</u>	LBP	115V 1PH 60Hz	1/4 HP	R-134a, R-513A	9.39
<u>AE2410Y-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/5 HP	R-134a	9.39
<u>AE2410Z-AA1A</u>	LBP	115V 1PH 60Hz	1/4 HP	R-404A, R-407A, R-448A, R-449A, R-452A	5.02
<u>AE2410Z-DS1A</u>	LBP	115-127V 1PH 60Hz	1/4 HP	R-404A	5.02
<u>AE2410Z-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/4 HP	R-404A	5.02
<u>AE2410Z-GS1A</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/4 HP	R-404A	5.02
<u>AE2413A-AA1B</u>	LBP	115V 1PH 60Hz	1/3 HP	R-12	12.01
<u>AE2413A-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/3 HP	R-401A	12.01
<u>AE2413U-AA1A</u>	LBP	115V 1PH 60Hz	1/3 HP	R-290	7.33

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE2413Y-AA1B</u>	LBP	115V 1PH 60Hz	1/3 HP	R-134a, R-513A	12.01
<u>AE2413Y-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/4 HP	R-134a	12.01
<u>AE2413Z-DS1A</u>	LBP	115-127V 1PH 60Hz	1/3 HP	R-404A	6.12
<u>AE2413Z-GS1A</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/3 HP	R-404A	6.12
<u>AE2415A-FZ1B</u>	LBP	220-240V 1PH 50Hz	1/2 HP	R-401A	12.48
<u>AE2415P-FZ1B</u>	LBP	220-240V 1PH 50Hz	1/3 HP	R-454C, R-455A	7.33
<u>AE2415U-AA1A</u>	LBP	115V 1PH 60Hz	1/3 HP	R-290	8.85
<u>AE2415U-FZ1A</u>	LBP	220-240V 1PH 50Hz	1/3 HP	R-290	8.85
<u>AE2415Y-FZ1B</u>	LBP	220-240V 1PH 50Hz	1/2 HP	R-134a	12.48
<u>AE2415Y-GH1B</u>	LBP	230V 1PH 50Hz	1/2 HP	R-134a	12.48
<u>AE2415Y-GH3C</u>	LBP	230V 1PH 50Hz	1/2 HP	R-134a	12.48
<u>AE2415Z-AA1A</u>	LBP	115V 1PH 60Hz	1/3 HP	R-404A, R-407A, R-448A, R-449A, R-452A	7.33
<u>AE2415Z-DS1A</u>	LBP	115-127V 1PH 60Hz	1/3 HP	R-404A	7.33
<u>AE2415Z-FZ1B</u>	LBP	220-240V 1PH 50Hz	1/3 HP	R-404A	7.33
<u>AE2415Z-GS1A</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/3 HP	R-404A, R-407A, R-448A, R-449A, R-452A	7.33
<u>AE2420P-FZ1B</u>	LBP	220-240V 1PH 50Hz	1/2 HP	R-454C, R-455A	9.33

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE2420U-AA1A</u>	LBP	115V 1PH 60Hz	1/2 HP	R-290	10.96
<u>AE2420U-FZ1B</u>	LBP	220-240V 1PH 50Hz	1/2 HP	R-290	10.96
<u>AE2420U-GS1B</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/2 HP	R-290	10.96
<u>AE2420Z-AA1B</u>	LBP	115V 1PH 60Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	9.35
<u>AE2420Z-DS1B</u>	LBP	115-127V 1PH 60Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	9.33
<u>AE2420Z-ES1A</u>	LBP	220V 1PH 60Hz	1/2 HP	R-404A	9.33
<u>AE2420Z-GS1B</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	9.33
<u>AE2425P-FZ1C</u>	LBP	220-240V 1PH 50Hz	1/2 HP	R-454C, R-455A	12.01
<u>AE2425Z-AA3C</u>	LBP	115V 1PH 60Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	12.01
<u>AE2425Z-FZ1C</u>	LBP	220-240V 1PH 50Hz	1/2 HP	R-404A	12.01
<u>AE2425Z-FZ3C</u>	LBP	220-240V 1PH 50Hz	1/2 HP	R-404A	12.01
<u>AE2425Z-GS3B</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	3/4 HP	R-404A	12.01
<u>AE2425Z-GS3C</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	3/4 HP	R-404A	12.01
<u>AE2430U-ES3C</u>	LBP	220V 1PH 60Hz	3/4 HP	R-290	14.51

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE2430Z-AA3C</u>	LBP	115V 1PH 60Hz	1 HP	R-404A	14.51
<u>AE2430Z-FZ3C</u>	LBP	220-240V 1PH 50Hz	1 HP	R-404A	14.51
<u>AE2430Z-GS3C</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz	1 HP	R-404A	14.51
<u>AE3425A-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/5 HP	R-12	6.69
<u>AE3425Y-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/5 HP	R-134a, R-513A	6.69
<u>AE3430Y-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/4 HP	R-134a, R-513A	8.02
<u>AE3440Y-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/3 HP	R-134a, R-513A	10.33
<u>AE3440Y-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/3 HP	R-134a	10.3
<u>AE3440Y-XN1A</u>	CBP, HBP	200-220V 1PH 50Hz, 208- 230V 1PH 60Hz	1/3 HP	R-134a, R-513A	10.33
<u>AE4425E-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/5 HP	R-22	4.24
<u>AE4425N-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/5 HP	R-1234yf, R- 134a	6.69
<u>AE4425P-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/5 HP	R-454C, R- 455A	4.24
Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE4425U-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/5 HP	R-290	5.02
<u>AE4425Y-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/5 HP	R-134a, R-513A	6.69
<u>AE4425Y-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/5 HP	R-134a	6.69

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE4425Y-GS1A</u>	CBP, HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/4 HP	R-134a, R-513A	6.69
<u>AE4425Z-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/5 HP	R-404A, R-407A, R-448A, R-449A, R-452A	4.24
<u>AE4425Z-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/5 HP	R-404A	4.24
<u>AE4425Z-GS1A</u>	HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/5 HP	R-404A	4.24
<u>AE4425Z-XN1A</u>	CBP, HBP	200-220V 1PH 50Hz, 208- 230V 1PH 60Hz	1/5 HP	R-404A, R-407A, R-448A, R-449A, R-452A	4.24
<u>AE4430A-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/4 HP	R-12	8.02
<u>AE4430E-DS1A</u>	CBP, HBP	115-127V 1PH 60Hz	1/4 HP	R-22	5.16
<u>AE4430E-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/4 HP	R-22	5.16
<u>AE4430E-GS1A</u>	CBP, HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/3 HP	R-22	5.16
<u>AE4430N-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/4 HP	R-1234yf, R-134a	8.02
<u>AE4430P-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/4 HP	R-454C, R-455A	5.16
<u>AE4430U-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/4 HP	R-290	6.12
<u>AE4430U-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/4 HP	R-290	6.12
<u>AE4430Y-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/4 HP	R-134a, R-513A	8.02
<u>AE4430Y-DS1A</u>	CBP, HBP	115-127V 1PH 60Hz	1/4 HP	R-134a	8.02

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE4430Y-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/4 HP	R-134a	8.02
<u>AE4430Y-GS1A</u>	HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/4 HP	R-134a	8.02
<u>AE4430Y-GT1A</u>	CBP, HBP	230V 1PH 50Hz, 230V 1PH 60Hz	1/4 HP	R-134a	8.02
<u>AE4430Y-XA1A</u>	CBP, HBP	100V 1PH 50Hz, 115V 1PH 60Hz	1/4 HP	R-134a, R-513A	8.02
<u>AE4430Y-XN1A</u>	CBP, HBP	200-220V 1PH 50Hz, 208- 230V 1PH 60Hz	1/4 HP	R-134a, R-513A	8.02
<u>AE4430Z-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/4 HP	R-404A, R- 407A, R-448A, R-449A, R- 452A	5.16
<u>AE4430Z-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/4 HP	R-404A	5.16
<u>AE4430Z-GS1A</u>	CBP, HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/4 HP	R-404A	5.16
<u>AE4435U-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/3 HP	R-290	6.91
<u>AE4440A-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/3 HP	R-12	10.33
<u>AE4440A-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/3 HP	R-401A	10.33
<u>AE4440E-DS1A</u>	CBP, HBP	115-127V 1PH 60Hz	1/3 HP	R-22	6.69
<u>AE4440E-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/4 HP	R-22	6.69
<u>AE4440E-GS1B</u>	HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/3 HP	R-22	6.69
<u>AE4440N-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/3 HP	R-1234yf, R- 134a	10.33

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE4440P-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/3 HP	R-454C, R-455A	6.69
<u>AE4440U-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/3 HP	R-290	8.02
<u>AE4440U-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/3 HP	R-290	8.02
<u>AE4440Y-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/3 HP	R-134a, R-513A	10.33
<u>AE4440Y-AC3C</u>	CBP, HBP	100-115V 1PH 60Hz, 100V 1PH 50Hz	1/3 HP	R-134a, R-513A	10.33
<u>AE4440Y-DS1A</u>	CBP, HBP	115-127V 1PH 60Hz	1/3 HP	R-134a	10.33
<u>AE4440Y-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/3 HP	R-134a, R-513A	10.33
<u>AE4440Y-GH1A</u>	CBP, HBP	230V 1PH 50Hz	1/3 HP	R-134a, R-513A	10.33
<u>AE4440Y-GH3C</u>	HBP	230V 1PH 50Hz	1/3 HP	R-134a	10.33
<u>AE4440Y-GS1A</u>	CBP, HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/3 HP	R-134a	10.33
<u>AE4440Y-GT1A</u>	HBP	230V 1PH 50Hz, 230V 1PH 60Hz	1/3 HP	R-134a	10.33
<u>AE4440Y-LS1A</u>	CBP, HBP	115V 1PH 60Hz	1/3 HP	R-134a, R-513A	10.33
<u>AE4440Y-UZ1A</u>	HBP	230V 1PH 50Hz, 230V 1PH 60Hz	1/3 HP	R-134a	10.33
<u>AE4440Y-XN1A</u>	CBP, HBP	200-220V 1PH 50Hz, 208- 230V 1PH 60Hz	1/3 HP	R-134a, R-513A	10.33
<u>AE4440Z-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/3 HP	R-404A, R-407A, R-448A, R-449A, R-452A	6.69

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE4440Z-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/3 HP	R-404A	6.69
<u>AE4440Z-GS1C</u>	HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/3 HP	R-404A	6.69
<u>AE4450A-FZ1C</u>	CBP, HBP	220-240V 1PH 50Hz	1/2 HP	R-401A	13.24
<u>AE4450E-DS1B</u>	CBP, HBP	115-127V 1PH 60Hz	1/2 HP	R-22	8.02
<u>AE4450E-FZ1B</u>	CBP, HBP	220-240V 1PH 50Hz	1/2 HP	R-22	8.02
<u>AE4450E-GS1B</u>	CBP, HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/3 HP	R-22	8.02
<u>AE4450N-FZ1C</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-1234yf, R-134a	13.24
<u>AE4450P-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/3 HP	R-454C, R-455A	8.85
<u>AE4450U-FZ1A</u>	HBP	220-240V 1PH 50Hz	1/3 HP	R-290	10.33
<u>AE4450Y-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/2 HP	R-134a, R-513A	13.24
<u>AE4450Y-DS1B</u>	CBP, HBP	115-127V 1PH 60Hz	1/2 HP	R-134a	13.24
<u>AE4450Y-ES1B</u>	CBP, HBP	220V 1PH 60Hz	1/2 HP	R-134a	13.24
<u>AE4450Y-FZ1B</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-134a	13.24
<u>AE4450Y-FZ1C</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-134a	13.24
<u>AE4450Y-GS3C</u>	CBP, HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/2 HP	R-134a	13.24
<u>AE4450Y-XA1A</u>	HBP	100V 1PH 50Hz, 115V 1PH 60Hz	1/2 HP	R-134a	13.24

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE4450Y-XN3C</u>	CBP, HBP	200-220V 1PH 50Hz, 208-230V 1PH 60Hz	1/2 HP	R-134a, R-513A	13.24
<u>AE4450Z-AA1A</u>	CBP, HBP	115V 1PH 60Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	8.85
<u>AE4450Z-AA3C</u>	CBP, HBP	115V 1PH 60Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	8.85
<u>AE4450Z-ES1B</u>	CBP, HBP	220V 1PH 60Hz	1/2 HP	R-404A	8.85
<u>AE4450Z-FS1B</u>	CBP, HBP	220V 1PH 50Hz	1/2 HP	R-404A	8.85
<u>AE4450Z-FZ1A</u>	CBP, HBP	220-240V 1PH 50Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	8.85
<u>AE4450Z-GS3B</u>	HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/2 HP	R-404A	8.85
<u>AE4450Z-XN3C</u>	CBP, HBP	200-220V 1PH 50Hz, 208-230V 1PH 60Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	8.85
<u>AE4456E-DS1B</u>	CBP, HBP	115-127V 1PH 60Hz	1/2 HP	R-22	9.39
<u>AE4456E-ES1B</u>	CBP, HBP	220V 1PH 60Hz	1/2 HP	R-22	9.39
<u>AE4456N-FZ1C</u>	HBP	220-240V 1PH 50Hz	1/3 HP	R-1234yf, R-134a	14.51
<u>AE4456Y-AA1C</u>	CBP, HBP	115V 1PH 60Hz	1/2 HP	R-134a, R-513A	14.51
<u>AE4456Y-FZ1C</u>	CBP, HBP	220-240V 1PH 50Hz	1/2 HP	R-134a	14.51
<u>AE4456Y-GS3C</u>	HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/2 HP	R-134a	14.51

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE4456Y-XN3C</u>	CBP, HBP	200-220V 1PH 50Hz, 208-230V 1PH 60Hz	1/2 HP	R-134a, R-513A	14.51
<u>AE4460E-DS1B</u>	CBP, HBP	115-127V 1PH 60Hz	1/2 HP	R-22	10.33
<u>AE4460E-ES1B</u>	CBP, HBP	220V 1PH 60Hz	1/2 HP	R-22	10.33
<u>AE4460E-FZ1B</u>	CBP, HBP	220-240V 1PH 50Hz	1/2 HP	R-22	10.33
<u>AE4460N-FZ1C</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-1234yf, R-134a	15.09
<u>AE4460P-FZ1B</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-454C, R-455A	10.33
<u>AE4460U-AA1C</u>	CBP, HBP	115V 1PH 60Hz	1/2 HP	R-290	12.01
<u>AE4460U-FZ1C</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-290	12.01
<u>AE4460Y-AA3C</u>	CBP, HBP	115V 1PH 60Hz	1/2 HP	R-134a, R-513A	15.09
<u>AE4460Y-FZ1C</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-134a	15.09
<u>AE4460Y-FZ3C</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-134a	15.09
<u>AE4460Y-GH3C</u>	HBP	230V 1PH 50Hz	1/2 HP	R-134a	15.09
<u>AE4460Y-GS3C</u>	HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/2 HP	R-134a	15.09
<u>AE4460Y-XB3C</u>	CBP, HBP	200V 1PH 50Hz, 230V 1PH 60Hz	1/2 HP	R-134a	15.09
<u>AE4460Z-AA1C</u>	CBP, HBP	115V 1PH 60Hz	1/2 HP	R-404A	10.33
<u>AE4460Z-FZ1C</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-404A	10.33

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AE4460Z-GS3C</u>	HBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/2 HP	R-404A	10.33
<u>AE4470E-ES3C</u>	CBP, HBP	220V 1PH 60Hz	3/4 HP	R-22	13.24
<u>AE4470E-FZ3C</u>	CBP, HBP	220-240V 1PH 50Hz	1/2 HP	R-22	13.24
<u>AE4470P-FZ3C</u>	HBP	220-240V 1PH 50Hz	1/2 HP	R-454C, R-455A	12.01
<u>AE4470Z-AA3C</u>	CBP, HBP	115V 1PH 60Hz	1/2 HP	R-404A, R-407A, R-448A, R-449A, R-452A	12.01
<u>AE4470Z-ES3C</u>	HBP	220V 1PH 60Hz	1/2 HP	R-404A	12.01
<u>AE4470Z-FS3C</u>	HBP	220V 1PH 50Hz	1/2 HP	R-404A	12.01
<u>AE4470Z-FZ3C</u>	CBP, HBP	220-240V 1PH 50Hz	1/2 HP	R-404A	12.01
<u>AE5465C-FZ3C</u>	AC, HBP	220-240V 1PH 50Hz	1/2 HP	R-407C	10.33
<u>AE5470C-FZ3C</u>	AC, HBP	220-240V 1PH 50Hz	1/2 HP	R-407C	12.01
<u>AEA1360AGS</u>	LBP	220V 1PH 50Hz, 220V 1PH 60Hz		R-12	7.55
<u>AEA2410AES</u>	LBP	220V 1PH 60Hz		R-12	12.04
<u>AEA2413ZKS</u>	LBP	220-240V 1PH 50Hz		R-404A	10.1
<u>AEA3440YDS</u>	HBP	115-127V 1PH 60Hz	1/3 HP	R-134a	12.04
<u>AEA4440YKS</u>	HBP	220-240V 1PH 50Hz		R-134a	12.04
<u>AEA5470EDS</u>	AC, HBP	100V 1PH 50Hz, 115- 127V 1PH 60Hz	1/2 HP	R-22	13.24


Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AEA9415EDS</u>	CBP	115-127V 1PH 60Hz	1/3 HP	R-22	5.67
<u>AEA9422EDS</u>	CBP	115-127V 1PH 60Hz	1/3 HP	R-22	7.57
<u>AEB1360AXA</u>	LBP	100V 1PH 50Hz, 115V 1PH 60Hz		R-12	7.55
<u>AED2413ZXA</u>	LBP	100V 1PH 50Hz, 115V 1PH 60Hz	1/2 HP	R-404A	11.3
<u>AED2414YGZ</u>	LBP	208-220V 1PH 50Hz	1/3 HP	R-134a	16
<u>AED2415ZHZ</u>	LBP	208-220V 1PH 60Hz	1/2 HP	R-404A	12.54
<u>AEW415Y- DS8B</u>	LBP, MBP	115-127V 1PH 60Hz	1/3 HP	R-134a	12.48
<u>AEW415Y- DS8C</u>	LBP, MBP	115-127V 1PH 60Hz	1/2 HP	R-134a	12.48
<u>AEW415Y- ES8A</u>	LBP, MBP	220V 1PH 60Hz	1/2 HP	R-134a	12.48
<u>AEW415Y- FZ8A</u>	LBP, MBP	220-240V 1PH 50Hz	1/3 HP	R-134a	12.48
<u>AEW415Y- GS8B</u>	LBP, MBP	220V 1PH 50Hz, 220V 1PH 60Hz	1/3 HP	R-134a	12.48
<u>AEX413Y- DS1B</u>	LBP	115-127V 1PH 60Hz	1/3 HP	R-134a, R- 513A	12.01
<u>AEX417U- DS1B</u>	LBP, MBP	115-127V 1PH 60Hz	1/3 HP	R-290	8.02
<u>AEX419U- DS1B</u>	LBP, MBP	115-127V 1PH 60Hz	1/2 HP	R-290	9.35
<u>AEX419U- FZ1C</u>	LBP, MBP	220-240V 1PH 50Hz	1/3 HP	R-290	10.33
<u>AEX424U- DS3C</u>	LBP, MBP	115-127V 1PH 60Hz	1/2 HP	R-290	12.01
<u>AEX424U- FZ3B</u>	LBP, MBP	220-240V 1PH 50Hz	1/2 HP	R-290	12.01

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AEX428U-DS3C</u>	LBP, MBP	115-127V 1PH 60Hz	3/4 HP	R-290	13.24

Model	Application	Voltage	Horse Power	Refrigerant	Displacement (CC)
<u>AEX428U-FZ3B</u>	LBP, MBP	220-240V 1PH 50Hz	1/2 HP	R-290	13.24
<u>AEX433U-AA3C</u>	LBP, MBP	115V 1PH 60Hz	3/4 HP	R-290	15.09
<u>AEX433U-DS3C</u>	LBP, MBP	115-127V 1PH 60Hz	3/4 HP	R-290	15.09
<u>AEX433U-FZ3C</u>	LBP, MBP	220-240V 1PH 50Hz	3/4 HP	R-290	15.09

[Mbsm Dot Pro Private PDFmbsm.pro Mbsmpro Compressor Tecumseh](#)

Attachments in this post:

Type	Link/Name
Image Attachment	
Attached File	<u>Mbsm_dot_pro_private_PDFmbsm.pro-Mbsmpro-Compressor-Tecumseh.pdf</u>
Link	<u>https://www.tecumseh.com/ProductFamily/AE/Catalog/product-type/compressors</u>
Link	<u>https://www.mbsm.pro/wp-content/uploads/2025/03/Mbsm_dot_pro_private_PDFmbsm.pro-Mbsmpro-Compressor-Tecumseh.pdf</u>